



### PYR-FA-CHA-RAP

REMOTE ANNUNCIATOR PANEL

The PYR-FA-CHA-RAP is a microprocessor based remote annunciator repeater panel that repeats all the information displayed on the main fire alarm control panel. The annunciator panel communicates with the main panel in real-time therefore the delay between data displayed on the main panel and the annunciator panel is only 3 seconds.

### **KEY FEATURES**

- Modern Design and Feel
- No Programming Required
- 4.3" Color LCD Display
- Displays the last 99 Events
- Can connect up to 20 remote annunciator panels to a single fire alarm control panel
- Remote annunciator panel is powered by the main fire alarm control panel
- 3 Year Warranty



## **SPECIFICATIONS**

#### **GENERAL**

Technology Microprocessor Based
Display 4.3" Color LCD Display

(480 x 272 Resolution)

Buttons 2 x Directions, Enter, Mute, Self-Test
LED Indicators Fire, Power, First Fire, Mute, and Comm.

Wiring 5 Wire Connection (24VDC, 0VDC, RS485 A, RS485 B, GND)

Tests Self-Test

#### **PERFORMANCE**

Communication RS485

Display History Latest 99 Events

Power Supply Supplied By Main Fire Alarm Control Panel

#### **ELECTRICAL**

Operating Voltage 19.2 to 28.8 VDC

Standby Current 34 mA Alarm Current 68 mA

#### **MECHANICAL**

Material High Impact Durable Engineered Polymer

Dimensions 210 mm x 150 mm x 33.5 mm

(Length x Width x Depth)

Weight 0.5 Kg

#### **ENVIRONMENTAL**

Application Indoor Installation Only Operating Temperature  $-10 \, ^{\circ}\text{C}$  to  $+50 \, ^{\circ}\text{C}$  Storage Temperature  $-10 \, ^{\circ}\text{C}$  to  $+55 \, ^{\circ}\text{C}$ 

Humidity 0 to 95% (Relative Humidity)

#### REGULATORY


Certification LPCB according to EN54-2 and EN54-4

Declaration CE






# **DIMENSIONS**



## **WIRING**






# **ORDERING INFORMATION**

Model	Description
PYR-FA-CHA-RAP	REMOTE ANNUNCIATOR PANEL





Email United States info@pyronics.us Website www.Pyronics.us

